

VI. MAIN AMPLIFIER ADJUSTMENT




Fig. 4 Main Amplifier P.C Board M2-5432A

Idling Current Adjustment

Connect a tester to Main Amplifier P.C Board test point between PIN-11 and PIN-12 (LEFT channel) and PIN-28 and PIN-29 (RIGHT channel).

Adjust semi-fixed resistors VR1, VR1b until the voltage is 30 mV.